

Date November 18, 1999

H

jc520 U.S. PTO
11/18/99

From
FULBRIGHT & JAWORSKI L.L.P.
2200 Ross Avenue, Suite 2800
Dallas, Texas 75201
214/855-8000

jc588 U.S. PTO
09/442853
11/18/99

PATENT APPLICATION TRANSMITTAL LETTER

Box PATENT APPLICATION
Assistant Commissioner
for Patents
Washington, D.C. 20231

"Express Mail" label no. EL31511056145

Date of Deposit: November 18, 1999

I hereby certify that this is being deposited with the United States Postal Service Express "Mail Post Office to Addressee" service under 37 CFR 1.10 on the date indicated above and is addressed to the Assistant Commissioner for Patents, Washington, D.C. 20231

By: Linda Cuccia

Printed/Typed Name: LINDA CUCCIA

Sir:

Transmitted herewith for filing under 37 C.F.R. 1.53(b) is a(n):

- ☒ Utility
- ☒ Original patent application,

Inventor(s): **Roger A. Babb, Kevin J. Krizman**

For: **CARRIER FREQUENCY COMPENSATION SYSTEM AND METHOD**

Enclosed are:

1. ☒ 33 pages of written description, claims and abstract.
2. ☒ 5 sheets of drawings.
3. ☒ Combined Declaration and Power of Attorney.
 - (a) ☒ Newly executed (original or copy)
 - (b) ☐ Copy from prior application (37 CFR 1.63(d)) (for continuation/divisional if Box 5 completed)

[Note Box 5 below]

4. ☐ Incorporation by Reference (useable if Box (b) is checked).

The entire disclosure of the prior application, from which a copy of the oath or declaration is supplied under Box 3(b), is considered as being part of the disclosure of the accompanying application and is hereby incorporated by reference therein.


5. ☐ If a **CONTINUING APPLICATION**, check appropriate box and supply the requisite information:
 - ☐ Continuation ☐ Divisional ☐ Continuation-in-part (CIP) of prior application Serial No:
6. ☒ Assignment Papers (cover sheet and document(s)) of the invention to Triton Network Systems, Inc.
7. ☐ A verified statement to establish small entity status under 37 CFR 1.9 and 37 CFR 1.27.
8. ☐ Information Disclosure Statement and Form PTO-1449. ☐ Copies of IDS Citations.
9. ☐ Preliminary Amendment

Date November 18, 199910. ☒ Return Receipt Postcard (MPEP 503) (should be specifically itemized)11. ☐ Certified Copy of Priority Document(s) (if foreign priority is claimed)12. ☐ Other: _____13. **Utility Fee Calculation**

CLAIMS	(1) FOR	(2) NUMBER FILED		(3)NUMBER EXTRA	(4) RATE		(5) CALCULATIONS	
	TOTAL CLAIMS (37 C F R. § 1 16(c) or (j))	37	- 20 =	17	X	\$ 9	=	153.00
	INDEPENDENT CLAIMS (37 C F R. § 1 16(b) or (i))	5	- 3 =	2	X	\$ 39	=	78.00
	MULTIPLE DEPENDENT CLAIMS (if applicable) (37 C.F.R. § 1.16(d))				+		=	
					Basic Fee			380.00
					Total of above Calculations =			611.00
	Reduction by 50% for filing by small entity (Note 37 C.F.R. §§ 1.9, 1.27 & 1.28)							
* Reissue claims in excess of 20 and over original patent					TOTAL =		\$611.00	
** Reissue independent claims over original patent								

Method of Fee Payment14. ☒ A check in the amount of \$611.00 to cover the filing fee is enclosed.15. ☒ A check in the amount of \$40.00 to cover the assignment recordal fee is enclosed.16. ☐ Please charge my Deposit Account No. 06-2380 in the total amount of the filing fee and the assignment recordation fee, if any. **A duplicate of this Transmittal Letter is enclosed, if box checked.**17. ☒ The Commissioner is hereby authorized to charge any deficiency in the enclosed fees under 37 C.F.R. § 1.16, or to charge any patent application processing fees under 37 C.F.R. § 1.17, or credit any overpayment, to Fulbright & Jaworski L.L.P. Deposit Account No. 06-2380.

Respectfully submitted,


 R. Ross Viguet
 Registration No. 42,203
 Counsel for Applicant
Date: 11-18-99
 Fulbright & Jaworski L.L.P.
 2200 Ross Avenue, Suite 2800
 Dallas, Texas 75201-2784
 Telephone: 214-855-8185
 Telecopier: 214-855-8200

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

- ☒ In re application of Applicant or Patentee: Roger A. Babb, KevinJ. Krizman
- ☐ Serial or Patent No.:
- ☐ Filed or Issued on:

Title: CARRIER FREQUENCY COMPENSATION SYSTEM AND METHOD

**STATEMENT CLAIMING SMALL ENTITY STATUS
(37 CFR 1.9(f) and 1.27(b))--SMALL BUSINESS CONCERN**

I hereby state that I am

- ☐ the owner of the small business concern identified below:
- ☒ an official of the small business concern empowered to act on behalf of the concern identified below:

Name of Small Business Concern Triton Network Systems, Inc.
Address of Small Business Concern 8529 Southpark Circle, 4th Floor
Orlando, Florida 32819

I hereby state that the above identified small business concern qualifies as a small business concern, as defined in 13 CFR 121.12, and reproduced in 37 CFR 1.9(d), for purposes of paying reduced fees to the United States Patent and Trademark Office under Sections 41(a) and (b) of Title 35, United States Code, in that the number of employees of the concern, including those of its affiliates, does not exceed 500 persons. For purposes of this statement, (1) the number of employees of the business concern is the average over the previous fiscal year of the concern of the persons employed on a full-time, part-time or temporary basis during each of the pay periods of the fiscal year, and (2) concerns are affiliates of each other when either, directly or indirectly, one concern controls or has the power to control the other, or a third-party or parties controls or has the power to control both.

I hereby state that rights under contract or law have been conveyed to, and remain with, the small business concern identified above, with regard to the invention described in

- ☒ the specification filed herewith, with title as listed above.
- ☐ the application identified above.
- ☐ the patent identified above.

If the rights held by the above-identified small business concern are not exclusive, each individual, concern or organization having rights in the invention is listed below* and no rights to the invention are held by any person, other than the inventor, who would not qualify as an independent inventor under 37 CFR 1.9(c), if that person made the invention, or by any concern which would not qualify as a small business concern under 37 CFR 1.9(d) or a nonprofit organization under 37 CFR 1.9(e).

Each such person, concern or organization having any rights in the invention is listed below:

- ☒ No such person, concern, or organization exists.
- ☐ Each such person, concern or organization is listed below.

Name _____
Address _____

☐ INDIVIDUAL ☐ SMALL BUSINESS CONCERN ☐ NONPROFIT ORGANIZATION

I acknowledge the duty to file, in this application or patent, notification of any change in status resulting in loss of entitlement to small entity status prior to paying, or at the time of paying, the earliest of the issue fee or any maintenance fee due after the date on which status as a small business entity is no longer appropriate. (37 CFR 1.28(b))

☒ I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further, that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code, and that such willful false statements may jeopardize the validity of the application, any patent issuing thereon, or any patent to which this verified statement is directed.

Name of Person Signing:
Title of Person if Other Than Owner:
Address of Person Signing:

Philip C. Gulliford
Vice President of Advanced Technology
8529 Southpark Circle, 4th Floor
Orlando, Florida 32819

SIGNATURE: *PCG*

Date: 10/22/99

CARRIER FREQUENCY COMPENSATION SYSTEM AND METHOD

Roger A. Babb
6016 Raleigh Street, Apt. 2903
Orlando, FL 32835
Citizenship: U.S.A.

Kevin J. Krizman
8708 Beckingham Place
Orlando, FL 32836
Citizenship: U.S.A.

REFERENCE TO RELATED APPLICATIONS

Reference is made to the following co-pending and commonly assigned U.S. Patent Application entitled COMMERCIAL NETWORK BASED ON POINT TO POINT RADIOS, Serial No. 09/245,701, filed February 6, 1999, the disclosure of which is incorporated herein by reference.

TECHNICAL FIELD

The present invention relates generally to point-to-point microwave communication systems and, more particularly, to an apparatus and method for compensating for long-term frequency drift between radio sites.

BACKGROUND

Point-to-point microwave radio systems are widely used to transmit data between and among two nodes of a communication link. The microwave radio system includes
5 microwave receivers and transmitters at both nodes of the system for transmitting and receiving data. Typically, data is received by a modem which modulates the data onto a baseband or intermediate frequency (IF) signal which is then up-converted to microwave frequencies, amplified and transmitted. The baseband or IF carrier is often provided by a phase-locked loop circuit which is locked to an IF oscillator or frequency synthesizer. In
10 turn, the frequency synthesizer is often provided with a reference oscillator which is also used for the up-conversion of the modulated IF signal to the microwave frequencies.

The microwave signal is received at a remote terminal station through an appropriate microwave radio front end circuit. The receiving radio circuitry receives a locally generated reference signal from a reference oscillator to down-convert the microwave radio signal to a
15 lower intermediate frequency or baseband signal to be demodulated so as to recover the digital data signal encoded onto the carrier signal. The demodulating modem uses a corresponding phase-locked loop circuit synchronized to the incoming baseband signal to recover the data. As in the transmitter circuit, the receiver's phase-locked loop circuit is similarly provided with an intermediate frequency signal from an IF oscillator or frequency
20 synthesizer which is also locked to the reference oscillator.

Minor signal frequency variations between sites are accommodated by the tracking capability of the receiver's phase-locked loop circuitry. The phase-locked loop (PLL) circuit generally includes a phase detector receiving a reference signal together with a sample of the output of the phase-locked loop circuit. The output of the phase detector is provided to a loop
25 filter which, in turn, provides an error signal controlling a voltage controlled oscillator (VCO). The VCO uses the error signal to maintain an output signal having a constant frequency defined by the feedback loop. This is accomplished by sampling the output signal provided by the VCO, dividing the frequency by a programmable counter, and then

comparing the frequency divided sample with the reference signal input at the phase detector to provide the error signal.

While the PLL can accommodate and adjust to some frequency variation of the reference signal, its operating range is still limited by certain design criteria. Thus, the PLL must receive an input signal which is within a predetermined capture or pull in range of its free running frequency prior to “locking in,” i.e., operating in a stable mode whereby the error signal provided by the phase detector and loop filter to the voltage control oscillator is within the range of the VCO’s operating capability. Once locked, the frequency of the reference signal must be maintained within a hold-in range of frequencies in which the PLL will remain locked to the signal. This range is also known as the lock limit of the PLL. The limited frequency range of the PLL provides a corresponding lock range of the receiver station in which changes of the frequency of the received signal in comparison to the local reference clock frequency can be accommodated. If the difference between the local reference frequency and the received signal becomes too great, the PLL will unlock and the modem will be unable to detect the digital data signal contained in the modulated carrier signal.

Referring to FIGURE 6, a radio communications terminal 100 transmits data over a microwave radio frequency link to radio communications terminal 200 which receives, detects and extracts the digital data for processing and/or retransmission to another site. Communications terminal 100 receives digital data at modulator 112 of modem 110. Modulator 112 further receives an IF carrier signal from phase-locked loop 114 and superimposes thereon the digital data signal to provide a modulated carrier signal to radio circuitry 140. Radio circuitry 140 up-converts, i.e., translates the modulated baseband or IF signal output provided by modulator 112 of modem 110 to a microwave frequency, amplifies and transmits the signal to a receiving terminal. Phase-locked loop 114 of modem 110 receives, and is locked to, an IF frequency signal provided by frequency synthesizer 120 which, in turn, is locked to a reference frequency signal provided by reference oscillator 130. Reference oscillator 130 also provides a signal to radio circuitry 140 to be used in up-converting the modulated IF signal to a microwave frequency signal, e.g., 38 GHz.

Communications terminal 200 includes radio circuitry 240 amplifying, filtering and down-converting the received microwave frequency signal received from transmitter terminal 100 to provide an IF or baseband output signal to demodulator 212 of modem 210.

Demodulator 212 receives the IF or baseband signal and, using a local oscillator signal provided by phase-locked loop 214, recovers the digital signal and provides the same as an output signal corresponding to the input signal of communications terminal 100. Phase-locked loop 214 of modem 210 is locked to an IF signal provided by local oscillator or frequency synthesizer 220 which, in turn, is locked to an output provided by reference oscillator 230. As in the case of the transmitting terminal, reference oscillator 230 is used both for demodulation and for down-conversion between microwave and IF frequencies.

When initially deployed, reference oscillator 130 of transmitting terminal 100 and reference oscillator 230 of receiving terminal 200 are adjusted to provide reference signals having the same nominal frequency or corresponding frequencies. However, the frequencies of the reference oscillators tend to slowly drift over time due to various factors, including component aging. To the extent these oscillators drift at different rates and/or in different directions over time, the nominal frequency of the microwave signal transmitted and the nominal center frequency of the receiving terminal will increasingly differ over time. Within the hold-in range capability of the phase-locked loop in the receiver, such variations can be accommodated by the receiving modem 210. However, as the frequency drift between the terminals becomes more severe, the ability of the receiving PLL to retain a lock on the IF signal provided by radio circuitry 240 will be exceeded and the communications link will fail. It will then be necessary to manually adjust or replace the reference oscillators in the transmitting and receiver terminals 100 and 200, respectively, to bring the system back into frequency alignment. During this time, of course, the radio communications link is inoperative.

Accordingly, a need exists for a communications system which is immune to or can accommodate long term frequency drift of its internal frequency standard reference. A still further need exists for a modem which can retain a locked condition over a wide range of IF input signals without requiring an automatic frequency control circuit to have a

disadvantageously wide capture, acquisition, or hold range capability. A still further need exists for a communications system which does not require expensive, highly stable reference frequency standards to operate properly and avoid loss of signal lock.

SUMMARY OF THE INVENTION

The present invention provides a communication modem, terminal and/or system which automatically compensates for long-term drift of the frequency standards or references used by the transmitting and receiver terminals so as to avoid manual adjustment of the terminals to bring them back within operating tolerances and minimize communications outages caused by the inability of the system to otherwise accommodate for such drift. The invention is usable over a broad range of media including the microwave region of the electromagnetic spectrum.

Briefly, the invention provides for automatic band selection to maintain a modulated carrier within the operating range of an automatic frequency control or tracking capability of a communication device such as a modem or other modulation device. This may be accomplished by selecting an appropriate reference signal used to control a center frequency of an automatic frequency control circuit (such as a phase-locked loop) or used to convert the carrier frequency of the modulated carrier to fall within the operating range of the automatic frequency control circuit and/or by causing the transmitting station to at least partially correct the frequency discrepancy.

According to one aspect of the invention, a communications terminal includes a modem receiving a modulated carrier signal. The modem preferably includes a carrier signal tracking circuit for continuously adjusting an actual center frequency of the modem about a nominal center frequency of the modem so as to cause the actual center frequency of the modem to correspond to a center frequency of the modulated carrier signal. The modem also preferably includes a controller which is responsive to the carrier signal tracking circuit for supplying a band select signal. A band selector is responsive to the band select signal for selecting one of a plurality of ranges of signal frequencies so as to cause the center frequency of the modulated carrier signal to be within one of the ranges including the nominal center frequency of the modem. According to a feature of the invention, the band selector provides a signal to the modem which defines the nominal center frequency of the modem. Alternatively, the band selector is operative to cause a frequency of the modulated carrier

signal to be converted so as to provide the modulated carrier signal having the center frequency of the carrier signal.

According to another feature of the invention, the communications terminal preferably includes an interface to a remote transmitter terminal providing the modulated carrier signal.

5 The communications terminal provides the remote transmitter terminal with a control signal over the interface to cause the remote transmitter terminal to change a frequency of the modulated carrier signal. According to a related feature of the invention, the communications terminal computes a frequency change value corresponding to a frequency change required to cause the modulated carrier signal to have a center frequency within a range of frequencies included in a median one of the plurality of ranges of signal frequencies. The
10 communications terminal preferably causes the remote transmitter terminal to change the frequency of the modulated carrier signal by approximately one-half of the frequency change value computed. Thus, each terminal changes frequency by approximately one-half of the total change required to bring the frequencies back into alignment.

15 According to another feature of the invention, the controller of the communications terminal preferably causes a frequency reference signal to be generated corresponding to a selected one of the plurality of ranges of signal frequencies including the actual center frequency of the modulated carrier signal.

20 According to another aspect of the invention, a communications terminal preferably includes a converter receiving a microwave radio signal and, in response, provides an intermediate frequency signal. A frequency synthesizer is responsive to a tuning signal for providing a local oscillator signal. The communications terminal further includes a modem receiving the intermediate frequency signal, the modem including a demodulator and a phase-locked loop circuit. The demodulator recovers a digital signal from the intermediate
25 frequency signal, while the phase-locked loop supplies a comparison signal in response to a comparison of a characteristic of the intermediate frequency signal and the local oscillator signal. A controller is responsive to the comparison signal to provide the tuning signal. The characteristic may be a phase relationship or a frequency of the signals. In the latter case, the

comparison signal is representative of a frequency difference between the transmitter carrier and the receiver's center frequency defined by its phase-locked loop.

According to another feature of the invention, the tuning signal preferably varies the frequency of the local oscillator signal in a plurality of discrete steps on either side of a nominal center frequency value. The phase-locked loop may be configured to lock to the intermediate frequency signal over a range of signal frequencies which are on the same order of magnitude as a frequency range between ones of the discrete steps. That is, the hold-in or capture range of frequencies for the phase-locked loop is approximately equal to or slightly greater than the step size used to adjust the operating frequency of the phase-locked loop. The steps may be equally spaced, having a frequency difference between steps within a range of 50 to 200 KHz.

According to another feature of the invention, the communications terminal further preferably includes an alarm corresponding to a predetermined value of the comparison signal. The controller may be responsive to the alarm for adjusting the tuning signal.

According to another feature of the invention, the communications terminal preferably includes a communication interface to a transmitting terminal originating the radio frequency signal. The controller negotiates with the transmitting terminal on the interface to change the frequency of the radio frequency signal by an amount such as that equal to approximately one-half of a frequency change required to bring the frequency of the radio signal within capture range of the phase-locked loop.

According to another feature of the invention, the controller preferably provides the tuning signal so as to deterministically affect the comparison signal, e.g., minimize the value of the offset error signal. The phase-locked loop is operable over a predetermined range of signal frequencies on either side of a nominal center frequency while the controller calculates a number of discrete steps required to minimize the offset error signal.

According to another feature of the invention, the controller supplies the tuning signal to correspond to the number of discrete steps calculated. Alternatively, according to another feature of the invention, the controller supplies the tuning signal to correspond to a portion of

the discrete steps calculated while communicating a remainder portion of the discrete steps calculated to a transmitter terminal originating the radio frequency signal.

According to another feature of the invention, the communications terminal further preferably includes a signal reacquisition routine which causes the frequency synthesizer to provide local oscillator signals having a predetermined sequence of frequencies. According to another feature of the invention, a reference frequency oscillator supplies a reference signal, whereby the converter additionally is responsive to the reference signal to provide the intermediate frequency signal. The frequency synthesizer is additionally responsive to the reference signal so as to provide the local oscillator signal.

According to another aspect of the invention, a communications terminal preferably includes a frequency synthesizer responsive to a tuning signal to provide a local oscillator signal. A modem includes a modulator which encodes a digital data signal onto the intermediate frequency signal as received. Also preferably included as part of the modem is a phase-locked loop circuit supplying an offset error signal in response to a difference between a frequency of the intermediate frequency signal and the frequency of the local oscillator signal. An up-converter receives the modulated intermediate frequency signal and, in response, provides a radio frequency signal. The communications terminal further includes a controller which is responsive to a frequency shift command signal from a remote terminal receiving the radio frequency signal to provide the tuning signal.

According to a feature of the invention, the terminal also preferably includes a reference frequency oscillator supplying a reference signal. The converter is responsive to the reference signal in addition to the intermediate frequency signal to provide the radio frequency signal. The frequency synthesizer is also responsive to the reference signal to provide the local oscillator signal.

According to another aspect of the invention, a preferred method of operating a communications terminal includes the steps of receiving a radio frequency signal, converting the radio frequency signal to an intermediate frequency signal, synthesizing a local oscillator signal in response to a tuning signal, comparing a frequency of the intermediate frequency signal and a frequency of a local oscillator signal to supply an offset error signal, providing

the tuning signal in response to the offset error signal, and recovering a digital data signal from the intermediate frequency signal.

According to a feature of the method, the step of providing the tuning signal preferably varies the frequency of the local oscillator signal in a plurality of discrete steps on either side of a nominal center frequency value. The method may additionally include a step of providing an alarm corresponding to a predetermined value of the offset signal and, in response, providing a tuning signal.

According to another feature of the invention, the preferred method further includes a step of negotiating with a transmitting terminal to change a frequency of the radio frequency signal by an amount equal to approximately one-half of a frequency change required to bring the frequency of the radio frequency signal within a predetermined capture range.

According to another aspect of the invention, a communications system includes transmitter and receiver terminals. The transmitter terminal preferably includes a first frequency synthesizer responsive to a first timing signal to provide a first local oscillator signal. A first modem receives the first local oscillator signal and a data signal. The first modem preferably includes a first phase-locked loop circuit supplying a first carrier signal in response to the first local oscillator signal and a modulator encoding a digital data signal onto the first intermediate frequency signal. The transmitter terminal also preferably includes an up-converter receiving the modulated carrier signal and, in response, providing a radio frequency signal. A first controller is responsive to an externally applied frequency shift command signal to provide the first tuning signal. The receiver terminal preferably includes a down-converter receiving the microwave signal to provide a second modulated carrier signal. A second frequency synthesizer is responsive to a second tuning signal to provide a second local oscillator signal used in the demodulation process. In particular, a second modem receives the second intermediate frequency signal which is applied to a demodulator for recovering the digital data signal therefrom. A second phase-locked loop circuit is preferably included as part of the second modem to supply an offset error signal in response to a difference between a frequency of the second intermediate frequency signal and the frequency of the second local oscillator signal. Finally, a second controller is preferably

responsive to the second offset error signal to supply the second tuning signal and the frequency shift command signal.

Although the present invention and its advantages have been described in detail, it should be understood that various changes, substitutions and alterations can be made herein without departing from the spirit and scope of the invention as defined by the appended
5 claims. Moreover, the scope of the present application is not intended to be limited to the particular embodiments of the process, machine, manufacture, composition of matter, means, methods and steps described in the specification. As one of ordinary skill in the art will readily appreciate from the disclosure of the present invention, processes, machines,
10 manufacture, compositions of matter, means, methods, or steps, presently existing or later to be developed that perform substantially the same function or achieve substantially the same result as the corresponding embodiments described herein may be utilized according to the present invention. Accordingly, the appended claims are intended to include within their scope such processes, machines, manufacture, compositions of matter, means, methods, or
15 steps.

BRIEF DESCRIPTION OF THE DRAWING

FIGURE 1 is a block diagram of a point-to-point microwave radio communications
5 system according to the invention;

FIGURE 2 is a process flow diagram of a method for performing frequency
compensation IF tuning;

FIGURE 3 is a process flow diagram of a method for performing transmitter IF
tuning;

FIGURE 4 is a process flow diagram of a method for assisting signal acquisition;

FIGURE 5 is a block diagram of a bidirectional point-to-point microwave link
according to the invention; and

FIGURE 6 is a block diagram of a point-to-point microwave system according to the
prior art.

DETAILED DESCRIPTION

FIGURE 1 is a block diagram of a point-to-point microwave radio system according to a preferred embodiment of the invention for transmitting information in the form of a data signal from a transmitter site A to a receiver site B. Typically the data signal is in the form of a digital data stream. The system preferably works in the 38 GHz range but is equally applicable to other frequencies, modes, and media of data transmission wherein receiver and transmitter facilities use distinct clock or frequency references which may drift with respect to each other, degrading or entirely inhibiting link performance. For simplicity of explanation, the embodiment of FIGURE 1 is shown as a unidirectional system for the transmission of data from transmitter site A to receiver site B, although, as will be detailed later, the invention is equally applicable to bidirectional, full duplex radio links and similar media having the aforementioned requirement to maintain a precise carrier frequency between and among transmitter and receiver stations.

Referring to FIGURE 1, a microwave transmitter terminal 300 of the preferred embodiment includes a transmitter modem 310, frequency synthesizer 320, reference oscillator 330, radio transmitter 340 and computer CPU (central processing unit) 350. Transmitter modem 310 includes a modulator 312 and phase-locked loop 314. Computer CPU 350 is connected to frequency synthesizer 320 for providing tuning commands and for receiving status information to/from frequency synthesizer 320. A frequency or time standard in the form of reference oscillator 330 is connected to frequency synthesizer 320 and radio circuitry 340 to provide a reference signal of a predetermined frequency or clock rate. In turn, frequency synthesizer 320 is connected to phase-locked loop 314 of modem 310.

Frequency synthesizer 320 is tunable, preferably in discrete steps under the control of transmitter computer CPU 350, e.g., in 100 KHz increments on either side of a predetermined center frequency. For example, frequency synthesizer 320 may be programmable to generate frequencies over a range of plus and minus 500 KHz in 100 KHz steps, the resultant carrier signal being provided to PLL 314. PLL 314 in combination with

modulator 312 receives the inputs from frequency synthesizer 320 and a digital data input signal to provide a modulated carrier signal to transmitter radio circuitry 340. Transmitter radio circuitry 340 up-converts and amplifies the modulated carrier signal to the desired transmission frequency range (e.g., 38 GHz). The amplified signal of this preferred
5 embodiment is radiated by directional microwave transmitter antenna 342 toward microwave radio receiver site B.

Microwave receiver terminal 400 at receiver site B receives the microwave RF transmission from microwave transmitter terminal 300 at directional microwave receiver antenna 442. Conventionally, a preamplifier and an initial down-converter may be located at or be part of directional microwave receiver antenna 442. Such circuitry may include
10 portions or all of microwave receiver terminal 400 which receives an output from antenna 442 at receiver radio circuitry 440. Using a master reference frequency signal from reference oscillator 430, radio circuitry provides an IF output to receiver modem 410. Reference oscillator 430 also provides a master reference or master frequency signal to frequency
15 synthesizer 420 which is responsive to tuning commands from receiver computer CPU 450 for providing a signal having a frequency of the nominal IF frequency to PLL 414 of receiver modem 410. PLL 414 in combination with demodulator 412 receives the IF signal from radio circuitry 440 to recover a baseband or demodulated signal, separated from the IF carrier signal. The demodulated baseband signal is then provided as an output to other terminal
20 equipment at the site (not shown) or for retransmission to a subsequent radio site, such as when deployed as part of a network as shown and described in the above referenced patent application entitled COMMERCIAL NETWORK BASED ON POINT TO POINT RADIOS. PLL 414 also preferably provides a carrier frequency offset error signal to receiver computer CPU 450 indicative of the frequency difference between the incoming reference carrier signal
25 provided by receiver radio circuitry 440 and a nominal center operating frequency of PLL as set by frequency synthesizer 420. Receiver computer CPU 450 is responsive to the error signal generated by PLL 414 to periodically change the frequency of the signal output by frequency synthesizer 420 to minimize the error signal received from PLL 414 and, thereby,

recenter its nominal operating frequency or otherwise optimize operation of PLL 414 to compensate for drift in the carrier signal relative to reference oscillator 430.

PLLs 314 and 414 may be conventional phase-locked loops including, for example, a phase detector receiving an input signal such as from frequency synthesizer 420. Generally, phase detector also receives a portion of the signal output by the PLL which has been divided by a programmable counter. When the PLL is "locked," the sample has a frequency and phase which is the same as, or in a predetermined constant relationship with, the reference frequency signal. The phase detector provides an output signal to a loop filter corresponding to the phase difference between these two signals. The loop filter provides a control signal analogous to an error signal to a voltage controlled oscillator to provide an output signal having a desired frequency. Because the output signal is sampled and processed to have a frequency which is substantially the same as the reference signal, the PLL uses a feedback loop to lock the frequency and phase of the output signal to that of the input signal to the PLL. When used as part of a demodulator, the PLL acts as a low pass filter to recover a baseband signal from a modulated carrier signal. Similarly, the PLL provides the appropriate IF frequency in a radio transmitter modem for modulation and subsequent up-conversion and transmission by the transmitter station.

In addition to providing an output for controlling frequency synthesizer 420, receiver computer CPU 450 also preferably provides control signaling to transmitter computer CPU 350 over communications link 452. Communications link 452 may be a dedicated network maintenance channel, a discrete RF back or control channel, or an overhead channel used by and/or available to the system as are described in the above referenced patent application entitled COMMERCIAL NETWORK BASED ON POINT TO POINT RADIOS. Using this link, receiver computer CPU 450, preferably in cooperation with compute CPU 350, can control both frequency synthesizers 320 and 420 to bring microwave transmitter terminal 300 and microwave receiver terminal 400 back into frequency alignment and, particularly, within the capture and frequency hold ranges of phase-locked loop 414 to maintain reception and demodulation of the digital data signals transported over the link. In a preferred embodiment, receiver computer CPU 450 monitors the carrier frequency offset from PLL 414 to

periodically or continuously select an appropriate offset frequency for frequency synthesizer 420. Alternatively, CPU 450 may await making adjustments to the output from synthesizer 420 until a predetermined maintenance period or in response to certain other network conditions. For example, CPU 450 may defer frequency adjustments until a period of low network use to avoid losing the communications link and creating a network outage which may result from reprogramming synthesizer 420.

Upon frequency synthesizer 420 reaching or approaching a maximum offset signal, or other predetermined threshold condition, or receiver computer CPU 450 requiring an offset amount greater than achievable by frequency synthesizer 420 alone, receiver computer CPU 450, preferably negotiates with transmitter computer CPU 350 to accomplish a desired adjustment. As a result, microwave transmitter terminal 300 and microwave receiver terminal 400 may each change frequency by approximately one-half of the total required to minimize the magnitude of frequency offset experienced and compensated by PLL 414.

Receiver modem 410 provides computer CPU 450 with the following variables in a most preferred embodiment to implement the frequency compensation method according to the invention, including:

1. Carrier frequency offset (FO): A signed scalar quantity indicating the frequency difference between the IF signal of the transmitter and that of the receiver.
2. Transmitter IF frequency (TF): The frequency of the baseband IF signal output by PLL 314 at the transmitter site A.
3. Receiver IF frequency (RF): The frequency of the signal provided by PLL 414 to demodulator 412.
4. Maximum transmitter IF frequency (MT): The maximum frequency offset effect from a predetermined nominal operating frequency achievable by corresponding changes to the output of frequency synthesizer 320 of microwave transmitter terminal 300.

5. Maximum receiver IF frequency (MR): The maximum offset frequency from a PLL nominal center frequency achievable by programming frequency synthesizer 420.
6. Carrier phase-locked indication (FLAG): A binary indicator of the locked/unlocked condition of PLL 414.

A portion of the processing performed to accomplish the frequency compensation method according to a preferred embodiment of the invention is shown in FIGURE 2. This process can be performed continuously, initiated in response to a maintenance feature, performed automatically when a predetermined high carrier frequency offset value is determined, performed at predetermined intervals, or the like. For example, receiver CPU 450 may initiate the frequency compensation procedure when the modem carrier offset exceeds 75% of the PLL lock range as indicated by a carrier frequency offset output FO from the modem. Alternatively, the procedure may be delayed until authorization is received from a network manager system so that any possible outage caused by the frequency compensation procedure, although unlikely depending on the speed of the circuitry instigating the change and that locking on the signal and, if occurring, only likely to be very brief, will be scheduled to minimize impact on network availability. Thus, the frequency compensation may be scheduled for a time period when network usage is minimal, non-critical, or backup systems are available and are operating to compensate for any system outage or interruption during the frequency compensation procedure. Upon initiation of the procedure of FIGURE 2 at entry point 500, flow continues to determine if the IF carrier signal received by modem 410 is phase-locked by PLL 414. If PLL 414 is unlocked, then the variable RF frequency is set to the last known value and processing continues at step 514 to initiate reacquisition of the carrier and associated IF signals.

If PLL 414 is operating in a locked mode, i.e., the IF frequency received from radio circuitry 440 is within the hold-in range of PLL 414 so that the output signal provided by PLL 414 is locked to the signal provided by frequency synthesizer 420, the process continues at step 504 where the carrier frequency offset value FO is obtained from receiver modem 410.

The carrier frequency offset FO represents the frequency difference between the receiver and transmitter input and output signals or the difference between their respective IF frequencies.

As previously discussed, prior art modems require that the receiver modem PLL be the sole resource for automatically compensating for deviation between transmitter and receiver frequencies. In contrast the invention (as shown at process 506) computes a new receiver IF frequency RF as being equal to the nominal receiver center frequency plus the carrier frequency offset FO rounded or truncated to the nearest 100 KHz (i.e., the step size used by frequency synthesizer 420 to adjust its output on either side of the nominal center frequency.) For example, according to one embodiment, PLL 414 may be controlled to achieve a maximum obtainable IF synthesizer frequency offset of plus or minus 500 KHz in 100 KHz increment steps by corresponding stepped changes to the output of frequency synthesizer 420 on either side of its nominal center frequency. Thus, the receiver IF frequency required to minimize PLL 414 offset is computed at step 506 and, at step 510, is compared with the maximum receiver IF frequency shift obtainable using frequency synthesizer 420. If the proposed offset falls within the capability of frequency synthesizer 420 (i.e., the absolute value of the computed radio IF frequency is less than or equal to the maximum receiver IF frequency MR), the processing continues at the start acquisition assistance flow diagram of FIGURE 4. Alternatively, if RF is greater than MR, then processing continues at step 512 which is expanded in the flow diagram of FIGURE 3. Thus, if the required frequency change falls outside the receiver's capabilities or desired operating range, then microwave receiver terminal 400 will, according to a preferred embodiment of the invention, negotiate with microwave transmitter terminal 300 to split the required offset by varying both the transmitter and receiver IF frequencies toward each other to minimize carrier frequency offset FO.

Of course, other divisions of the desired offset may be employed, if desired. For example, as a preferred embodiment utilizes a maximum amount of available adjustment at a receiver location before exploiting communication resources and transmitter adjustment resources to distribute the desired offset, or alternative embodiment may operate to initially provide all or most offset at a transmitter location to lengthen the interval until a next such

negotiation occurs. Moreover, such negotiations may consider information in addition to an amount of offset desired. For example, historical information, such as a direction of drift (i.e., increase or decrease in frequencies) of either or both ends of the link, a speed or rate at which drift has been experienced, or the like may be considered in order to better delegate the desired offset, such as to minimize a number of such further negotiations, etc.

A flow chart of a preferred embodiment of the IF tuning method coordinating adjustment of the transmitter frequency is shown in FIGURE 3. If the IF synthesizer in the receiver has exceeded its tuning capability, the required frequency compensation may be achieved by tuning the IF synthesizer in the transmitter in conjunction with the IF synthesizer in the receiver. If the required IF tuning cannot be accommodated by a proper adjustment of both the transmit and receive IF synthesizers, a fault is preferably indicated.

In particular, adjustment of the transmitter IF frequency is initiated at step 520, the previously computed receiver IF frequency RF being read at step 522 and the corresponding transmitter frequency representing half of the required frequency shift is computed at step 524. That is, the transmitter IF frequency is determined to be its nominal transmitter IF frequency TF minus one-half of the receiver IF frequency previously computed. The remainder of the frequency adjustment required is computed at step 526 by setting the receiver IF frequency equal to its nominal value plus one-half of the computed value. A check is performed at step 528 to determine if the computed transmitter IF frequency is within the maximum transmitter IF frequency for the system. If the computed transmitter IF frequency falls outside of this range so that frequency synthesizer 320 cannot accommodate the frequency adjustment, then an error message is generated at step 530. Otherwise, processing continues with the start acquisition process at step 532 as will be more fully explained with reference to FIGURE 4.

FIGURE 4 is a flow chart of the acquisition assist process of a preferred embodiment of the present invention. When acquisition assistance is initiated, receiver modem 410 begins by trying for a predetermined time, such as up to 0.5 seconds, to lock to the received carrier. If signal lock is not achieved, the receive modem attempts to lock by repeatedly tuning the IF frequency synthesizer 420 further and further from the current center frequency until lock is

attained, the acquisition assist process times out, or no lock is attained and further IF frequency tuning is not possible. If a lock is achieved, the link will return to service. If a lock is not achieved, the process continues to attempt a lock, but a critical alarm due to a link out of service condition will persist until lock-up is achieved. Such an alarm may operate to cause synthesizer 320 to also begin tuning to various IF frequencies in order to assist modem 410 in locking to the received carrier.

Referring to FIGURE 4, the start acquisition assistance process is entered at step 540 and the variables used to step through the process are initialized at step 542. In particular, the receiver IF frequency is set as previously computed by the frequency compensation IF tuning process of FIGURE 2 or the receiver and transmitter IF tuning process of FIGURE 3. Loop variables k and N are set, k being a binary value indicating the direction of each progressive offset and N indicating the magnitude of each offset from the value RF previously computed.

Step 544 is the top of a "while" loop ending with carrier lock at decision box 548. The while loop is entered at step 544 where the appropriate step value is added to or subtracted from the receiver IF frequency depending on the current value for k . Initially, upon loop entry, $N = 0$ and $k = 0$ so that there is no change to the receiver IF frequency RF . The process then preferably waits for 0.5 seconds at step 546 to provide time for PLL 414 to capture the signal and lock to it. If lock is achieved, then the while loop is exited and the process terminates at step 562. If, however, PLL 414 is unable to lock to the IF frequency, then the process sequentially steps the value of RF in increasing magnitudes on both sides of the center frequency RF until frequency lock is attained or the combined capability of the transmitter modem and receiver modem to converge is exceeded. Thus, at step 550, if $k = 1$ (indicating that the current offset had already been used to increment the value of RF), then k is reset to be equal to zero at step 556 so that the value of N is used to decrement the value of RF the next time through process step 544. Alternatively, if k is not equal to one, i.e., $k = 0$, then processing continues out of the top of decision step 550 to set k equal to one at step 552 and to increment N at 554. A check is then performed at decision step 558 to determine if the value of RF when incremented by the current value of N would exceed the maximum receiver IF frequency MR . If the value of RF when incremented by N falls within the capability of the

receiver, i.e., is less than or equal to the maximum receiver IF frequency, then processing continues at process step 544 to attempt a lock. Otherwise, processing continues out of the top of decision step 558 to initiate transmitter IF tuning to attempt to converge the transmitter frequency to the receiver frequency as previously described in connection with FIGURE 3.

5 As previously explained, the transmitter IF tuning process preferably has receiver CPU 450 instruct transmitter CPU 350 to adjust the frequency of frequency synthesizer 320 to shift frequency one-half of the total required to bring transmitter modem 310 and receiver modem 410 into frequency alignment to a degree whereby PLL 414 can achieve a locked condition at step 548.

10 FIGURE 5 depicts a bidirectional embodiment of the invention wherein microwave sites 300a and 400a each include receiver and transmitter capabilities and an existing site-to-site overhead channel may be used to coordinate automatic alignment of the systems to maintain or reacquire lock by PLLs 364 and 464. In this configuration, one of the sites may be designated as a master and the other a slave. For example, even though microwave radio facility 400a has both receive and transmitter capabilities, it would perform the frequency compensation process earlier detailed for the receiver terminal whereas facility 300a would perform those functions detailed in connection with the microwave transmitter terminal. 15 Alternatively, each radio site might perform processing to maintain lock on its receive signal independently of the far transmitter station in each case.

20 Although several embodiments of the invention have been described in detail above, it should be clear that the present invention is capable of numerous modifications as would be apparent to one of ordinary skill in the art. Such modifications fall within the purview of the appended claims. For example, the invention is equally applicable to point-to-multipoint radio systems in general and to other media of communication wherein gross frequency 25 alignment between a transmitter and one or more receivers is achieved using one capability such as the programmable frequency synthesizer described in the embodiments above, and real time fine alignment is achieved by alternate means such as the PLLs according to those embodiments. Thus, the invention is applicable to all such tunable communications devices including, for example, an automatic frequency control system of limited range augmented by

a gross frequency adjustment facility such that frequency alignment between terminals is maintained and, as necessary, reacheived. Moreover, there is no limitation of the present invention to its use with wireless or even radio frequency communications. For example, the concepts of the present invention are applicable to wired communication systems utilizing modulated signals. Additionally, electro magnetic modulation of signals is not required for the advantages of the present invention to be realized, as these concepts are applicable to other modulation techniques, such as light or optic transmission of data.

Although the present invention and its advantages have been described in detail, it should be understood that various changes, substitutions and alterations can be made herein without departing from the spirit and scope of the invention as defined by the appended claims. Moreover, the scope of the present application is not intended to be limited to the particular embodiments of the process, machine, manufacture, composition of matter, means, methods and steps described in the specification. As one of ordinary skill in the art will readily appreciate from the disclosure of the present invention, processes, machines, manufacture, compositions of matter, means, methods, or steps, presently existing or later to be developed that perform substantially the same function or achieve substantially the same result as the corresponding embodiments described herein may be utilized according to the present invention. Accordingly, the appended claims are intended to include within their scope such processes, machines, manufacture, compositions of matter, means, methods, or steps.

WHAT IS CLAIMED IS:

1. A communications terminal comprising:
a modem receiving a modulated carrier signal and including a carrier signal tracking circuit
for continuously adjusting an actual center frequency of said modem about a nominal
center frequency of said modem so as to cause said actual center frequency of said
modem to correspond to a center frequency of said modulated carrier signal;
a controller responsive to said carrier signal tracking circuit for supplying a band select
signal; and
a band selector responsive to said band select signal for selecting one of a plurality of ranges
of signal frequencies so as to cause said center frequency of said modulated carrier
signal to be within one of said ranges including said nominal center frequency of said
modem.
2. The communications terminal according to claim 1 wherein said band selector
provides a signal to said modem defining said nominal center frequency.
3. The communications terminal according to claim 1 wherein said band selector
causes a frequency of said modulated carrier signal to be converted so as to provide said
modulated carrier signal having said center frequency of said carrier signal.
4. The communications terminal according to claim 1 further comprising an
interface to a remote transmitter terminal providing said modulated carrier signal, said
communications terminal providing said remote transmitter terminal with a control signal
over said interface causing said remote transmitter terminal to change a frequency of said
modulated carrier signal.
5. The communications terminal according to claim 4 wherein said
communications terminal computes a frequency change value corresponding to a frequency

change required to cause said modulated carrier signal to have a center frequency within a range of frequencies included in a median one of said plurality of ranges of signal frequencies and wherein said communications terminal causes said remote transmitter terminal to change said frequency of said modulated carrier signal by approximately one half of said frequency change value.

6. The communications terminal according to claim 1 wherein said controller causes a frequency reference signal to be generated corresponding to a selected one of said plurality of ranges of signal frequencies including said actual center frequency of said modulated carrier signal.

7. A radio communications terminal comprising:
a converter receiving a radio frequency signal and, in response, providing an
intermediate frequency signal;
a frequency synthesizer responsive to a tuning signal for providing a local oscillator
5 signal;
a radio modem receiving said intermediate frequency signal and including
(i) a demodulator recovering a digital data signal from said intermediate frequency
signal, and
(ii) a phase-locked loop comparing a characteristic of said local oscillator and
intermediate frequency signals and, in response, providing a comparison signal; and
10 a controller responsive to said comparison signal for providing said tuning signal.

8. The radio communications system according to claim 7 wherein said
characteristic is a phase relationship.

9. The radio communications system according to claim 7 wherein said
characteristic is frequency.

10. The radio communication terminal according to claim 7 wherein said tuning
signal varies said frequency of said local oscillator signal in a plurality of discrete steps on
either side of a nominal center frequency value.

11. The radio communication terminal according to claim 10 wherein said phase-
locked loop is configured to lock to said intermediate frequency signal over a range of signal
frequencies which is on the same order of magnitude as a frequency range between ones of
said discrete steps.

12. The radio communication terminal according to claim 10 wherein said discrete steps are equally spaced, having a frequency difference between steps within a range of 50 to 200 kilohertz.

13. The radio communication terminal according to claim 7 further including an alarm corresponding to a predetermined value of said comparison signal.

14. The radio communication terminal according to claim 13 wherein said controller is responsive to said alarm for adjusting said tuning signal.

15. The radio communication terminal according to claim 7 further including a communication interface to a transmitting terminal originating said radio frequency signal, said controller negotiating with said transmitting terminal on said interface to change a frequency of said radio frequency signal by an amount equal to approximately one-half of a frequency change required to bring a frequency of said intermediate frequency signal within a capture range of said phase-locked loop.

16. The radio communication terminal according to claim 7 wherein said controller provides said tuning signal so as to produce a desired effect on said comparison signal.

17. The radio communication terminal according to claim 16 wherein said phase-locked loop is operable over a predetermined range of signal frequencies on either side of a nominal center frequency and said controller calculates a number of said discrete steps required so as to produce a desired effect on said comparison signal.

18. The radio communication terminal according to claim 17 wherein said controller supplies said tuning signal to correspond to said number of said discrete steps calculated.

19. The radio communication terminal according to claim 17 wherein said controller supplies said tuning signal to correspond to a portion of said discrete steps calculated and communicates a remaining portion of said discrete steps calculated to a transmitter terminal originating said radio frequency signal.

20. The radio communications terminal according to claim 7 wherein said controller includes a signal reacquisition routine causing said frequency synthesizer to provide local oscillator signals having a predetermined sequence of frequencies.

21. The radio communications terminal according to claim 7 further comprising a reference frequency oscillator supplying a reference signal, said converter additionally responsive to said reference signal for providing said intermediate frequency signal and said frequency synthesizer additionally responsive to said reference signal for providing said local oscillator signal.

22. A radio communications terminal comprising:
a frequency synthesizer responsive to a tuning signal for providing a local oscillator
signal;
a radio modem receiving said local oscillator signal and including
5 (i) a phase-locked loop circuit receiving said local oscillator signal and, in response,
providing a carrier signal, and
(ii) a modulator encoding a data signal onto said carrier signal to provide a modulated
carrier signal;
a converter receiving said modulated carrier signal and, in response, providing a radio
10 frequency signal; and
a controller responsive to a frequency shift command signal from a remote terminal
receiving said radio frequency signal for providing said tuning signal.

23. The radio communications terminal according to claim 22 further comprising
a reference frequency oscillator supplying a reference signal, said converter additionally
responsive to said reference signal for providing said radio frequency signal and said
frequency synthesizer additionally responsive to said reference signal for providing said local
5 oscillator signal.

24. The radio communication terminal according to claim 22 wherein said tuning
signal varies said frequency of said local oscillator signal in a plurality of discrete steps on
either side of a nominal center frequency value.

25. The radio communication terminal according to claim 24 wherein said phase-
locked loop is configured to lock to said intermediate frequency signal over a range of signal
frequencies which is on the same order of magnitude as a frequency range between ones of
said discrete steps.

26. The radio communication terminal according to claim 24 wherein said discrete steps are equally spaced, having a frequency difference between steps within a range of 50 to 200 kilohertz.

27. The radio communication terminal according to claim 22 wherein said phase-locked loop additionally provides an error signal, said controller responsive to said error signal for adjusting said tuning signal.

28. A method of operating a radio communications terminal comprising the steps
of:

receiving a radio frequency signal;
converting said radio frequency signal to an intermediate frequency signal;
5 synthesizing a local oscillator signal in response to a tuning signal;
comparing a frequency of said intermediate frequency signal and a frequency of said
local oscillator signal to supply an offset error signal;
providing said tuning signal in response to said offset error signal; and
recovering a digital data signal from said intermediate frequency signal.

29. The method according to claim 28 wherein said step of providing said tuning
signal varies said frequency of said local oscillator signal in a plurality of discrete steps on
either side of a nominal center frequency value.

30. The method according to claim 28 further including a step of providing an
alarm corresponding to a predetermined value of said offset error signal.

31. The method according to claim 30 wherein said step of providing said tuning
signal is performed in response to said alarm for adjusting said tuning signal.

32. The method according to claim 28 further comprising the step of negotiating
with a transmitting terminal to change a frequency of said radio frequency signal by an
amount equal to approximately one-half of a frequency change required to bring said
frequency of said intermediate frequency signal within a predetermined capture range.

33. A radio communications system comprising:

(a) a transmitter terminal including

(i) a first frequency synthesizer responsive to a first tuning signal for providing a first local oscillator signal;

(ii) a first radio modem receiving said first local oscillator signal and including a first phase-locked loop circuit supplying a carrier signal in response to said first intermediate frequency signal, and

a modulator encoding a data signal onto said carrier signal to supply a first modulated carrier signal;

(iii) an up-converter receiving said first modulated carrier signal and, in response, providing a radio frequency signal; and

(iv) a first controller responsive to a frequency shift command signal for providing said first tuning signal; and

(b) a receiver terminal including

(i) a down-converter receiving said radio frequency signal and, in response, providing a second modulated carrier signal;

(ii) a second frequency synthesizer responsive to a second tuning signal for providing a second local oscillator signal;

(iii) a second radio modem receiving said modulated carrier signal and including

a second phase-locked loop circuit responsive to said second local oscillator signal to supply (a) a second intermediate frequency signal and (b) an offset error signal in response to a difference between a frequency of said second modulated carrier signal and a frequency of said second intermediate frequency signal, and

a demodulator recovering said data signal from said second modulated carrier signal; and

(iv) a second controller responsive to said offset error signal for providing said second tuning signal and said frequency shift command signal.

34. The radio communication system according to claim 33 wherein said first and second tuning signals vary respective ones of said frequencies of said first and second local oscillator signals in a plurality of discrete steps on either side of respective nominal center frequency values.

35. The radio communication system according to claim 33 further including an alarm corresponding to a predetermined value of said offset error signal.

36. The radio communication system according to claim 35 wherein said second controller is responsive to said alarm for adjusting said second tuning signal and for providing said frequency shift command signal.

37. The radio communication terminal according to claim 33 wherein said second controller negotiates with said first controller to change a frequency of said radio frequency signal by an amount equal to approximately one-half of a frequency change required to bring said frequency of said second modulated carrier signal within a capture range of said second phase-locked loop.

CARRIER FREQUENCY COMPENSATION SYSTEM AND METHOD**ABSTRACT OF THE DISCLOSURE**

A radio modem for use in a communications system monitors an error signal generated by the modem's phase-locked loop (PLL) used to demodulate an IF frequency signal and recover a digital data signal. If, due to long-term drift of a reference oscillator of the receiver or due to transmitter frequency drift, the PLL error signal exceeds a
5 predetermined value typically corresponding to 75% of its hold-in or lock maintenance range, a carrier frequency compensation process is initiated to recenter the PLL on the current IF signal by reprogramming a frequency synthesizer supplying the PLLs input signal. A CPU causes the frequency synthesizer to increment or decrement the frequency of the signal provided to the PLL to bring the operating frequency of the PLL closer to that of the IF
10 signal. If the required frequency compensation falls outside the tuning range of the receiving modem, either because the frequency synthesizer is unable to generate the required frequency or because of excessive shift of the IF frequency, then the receiver terminal negotiates with the corresponding transmitter terminal to converge both IF frequencies. As a result, the transmitter changes its frequency by an amount equal to one-half of the required frequency
15 shift while the receiver terminal performs the remainder of the frequency shift. Upon reprogramming of one or both synthesizers to readjust the operating frequencies of the receiver and/or transmitter, the receiver performs a search process to reacquire lock on the transmitter, starting at the predicted IF center frequency and alternately scanning in increasing amounts away from and on either side of the predicted center frequency until a
20 signal lock is achieved or until a timeout occurs.

FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5





FIG. 6
(PRIOR ART)



COMBINED DECLARATION AND POWER OF ATTORNEY

(ORIGINAL, DESIGN, NATIONAL STAGE OF PCT, SUPPLEMENTAL, DIVISIONAL,
CONTINUATION, OR C-I-P)

As a below named inventor, I hereby declare that:

TYPE OF DECLARATION

This declaration is of the following type:

- ☒ original.
- ☐ design.
- ☐ supplemental.
- ☐ national stage of PCT.
- ☐ divisional.
- ☐ continuation.
- ☐ continuation-in-part (C-I-P).

INVENTORSHIP IDENTIFICATION

My residence, post office address and citizenship are as stated below, next to my name. I believe that I am the original, first and sole inventor (*if only one name is listed below*) or an original, first and joint inventor (*if plural names are listed below*) of the subject matter that is claimed, and for which a patent is sought on the invention entitled:

TITLE OF INVENTION

CARRIER FREQUENCY COMPENSATION SYSTEM AND METHOD

SPECIFICATION IDENTIFICATION

The specification of which:

- (a) ☒ is attached hereto.
- (b) ☐ was filed on _____ as ☐ Serial No. _____ or
☐ _____ and was amended on _____ (*if applicable*).
- (c) ☐ was described and claimed in PCT International Application No. _____ filed on _____ and as amended under PCT Article 19 on _____ (*if any*).

SUPPLEMENTAL DECLARATION (37 CFR 1.67(b))

- ☐ I hereby declare that the subject matter of the
- ☐ attached amendment
- ☐ amendment filed on _____.

was part of my/our invention and was invented before the filing date of the original application, above identified, for such invention.

ACKNOWLEDGMENT OF REVIEW OF PAPERS AND DUTY OF CANDOR

I hereby state that I have reviewed and understand the contents of the above-identified specification, including the claims, as amended by any amendment referred to above.

I acknowledge the duty to disclose information, which is material to patentability as defined in 37, Code of Federal Regulations, § 1.56,

- ☐ in compliance with this duty, there is attached an information disclosure statement, in accordance with 37 CFR 1.98.

PRIORITY CLAIM (35 U.S.C. § 119(a)-(d))

I hereby claim foreign priority benefits under Title 35, United States Code, § 119(a)-(d) of any foreign application(s) for patent or inventor's certificate or of any PCT international application(s) designating at least one country other than the United States of America listed below and have also identified below any foreign application(s) for patent or inventor's certificate or any PCT international application(s) designating at least one country other than the United States of America filed by me on the same subject matter having a filing date before that of the application(s) of which priority is claimed.

- (d) ☒ no such applications have been filed.
- (e) ☐ such applications have been filed as follows.

**PRIOR FOREIGN/PCT APPLICATION(S) FILED WITHIN 12 MONTHS
(6 MONTHS FOR DESIGN) PRIOR TO THIS APPLICATION
AND ANY PRIORITY CLAIMS UNDER 35 U.S.C. § 119(a)-(d)**

COUNTRY (OR INDICATE IF PCT)	APPLICATION NUMBER	DATE OF FILING DAY, MONTH, YEAR	PRIORITY CLAIMED UNDER 35 USC 119
			[] YES [] NO
			[] YES [] NO

CLAIM FOR BENEFIT OF PRIOR U.S. PROVISIONAL APPLICATION(S)
(35 U.S.C. § 119(e))

I hereby claim the benefit under Title 35, United States Code, § 119(e) of any United States provisional application(s) listed below:

PROVISIONAL APPLICATION NUMBER**FILING DATE**

CLAIM FOR BENEFIT OF EARLIER U.S./PCT APPLICATION(S)
UNDER 35 U.S.C. § 120

☐ The claim for the benefit of any such applications are set forth below:

APPLICATION SERIAL	FILING DATE	STATUS

ALL FOREIGN APPLICATION(S), IF ANY, FILED MORE THAN 12 MONTHS
(6 MONTHS FOR DESIGN) PRIOR TO THIS U.S. APPLICATION

POWER OF ATTORNEY

I hereby appoint the following practitioner(s) to prosecute this application and transact all business in the Patent and Trademark Office connected therewith:

David H. Tannenbaum, Reg. No. 24,745;
Michael A. Papalas, Reg. No. 40,381;
R. Ross Viguet, Reg. No. 42,203;
Michael J. Fogarty, III, Reg. No. 42,541
Brian A. Carlson, Reg. No. 37,793
Jody Bishop, Reg. No. 44,034

SEND CORRESPONDENCE TO

David H. Tannenbaum
FULBRIGHT & JAWORSKI L.L.P.
2200 Ross Avenue, Suite 2800
Dallas, Texas 75201

DIRECT TELEPHONE CALLS TO:

David H. Tannenbaum
(214) 855-8333

DECLARATION


I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code, and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

SIGNATURE(S)

NOTE: Carefully indicate the family (or last) name, as it should appear on the filing receipt and all other document.

Full name of sole or first inventor: Roger A. Babb

Inventor's signature



Country of Citizenship: U.S.A.


Date: 11 November 1999

Residence 6016 Raleigh Street, Apt. 2903, Orlando, FL 32835

Post Office Address: 6016 Raleigh Street, Apt. 2903, Orlando, FL 32835

Full name of sole or first inventor: Kevin J. Krizman

Inventor's signature



Country of Citizenship: U.S.A.

Date: 10. NOVEMBER, 1999

Residence 8708 Beckingham Place, Orlando, FL 32836

Post Office Address: 8708 Beckingham Place, Orlando, FL 32836